



mpt300_en 08/17

The MPT-300 keyfob allows you to control the alarm system or automation devices. The keyfob is supported by:

- alarm module MICRA (firmware version 2.02 or newer),
- 433 MHz keyfobs receiver expansion module INT-RX-S,
- 433 MHz wireless system controller VERSA-MCU,
- 433 MHz wireless system controller MTX-300,
- SATEL radio remote controllers.

For information on how to add the keyfobs and functions you can perform by using them, please refer to the manuals of devices that support the MPT-300 keyfobs.

1. Features

- Transmissions secured by KeeLoq code hopping.
- 5 buttons to run up to 6 selected functions.
- Key press LED indicator.

2. Specifications

Operating frequency band	433,05 ÷ 434,79 MHz
Radio communication range (in open area)	up to 100 m
Battery	2 x CR2016 3V
Environmental class according to EN50130-5	II
Operating temperature range	-10 °C...+55 °C
Maximum humidity	93±3%
Enclosure dimensions	38 x 78 x 16 mm
Weight	30 g

Hereby, SATEL sp. z o.o., declares that this keyfob is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU. The declaration of conformity may be consulted at www.satel.eu/ce

3. Battery replacement



There is a danger of battery explosion when using a different battery than recommended by the manufacturer, or handling the battery improperly.

Be particularly careful during installation and replacement of the battery. The manufacturer is not liable for the consequences of incorrect installation of the battery.

The used batteries must not be discarded, but should be disposed of in accordance with the existing rules for environment protection.

The battery life depends on how the keyfob is used. The more frequently the buttons are pressed, the faster the battery is draining. Each transmission sent from the keyfob contains information on the battery status. Devices that support the keyfob can indicate that the battery is low. How to replace the battery is shown in the figures below.

