

# PRF-LCD-WRL

PRF-LCD-WRL is a wireless keypad designed for daily operation of the **PERFECTA** control panels (equipped with **PERFECTA-RF** module or **WRL** models). Two-way encrypted communication with the control panel takes place at 433 MHz. The device meets the EN 50131 security requirements for Grade 2. Big keys, LCD display and LEDs indicating the system status make operation of the system easy and clear for all users. In addition to the number keys, the keypad has also buttons for quick activation of the selected armed mode (day, night, full) and triggering of three alarms: Panic, Fire, Aux. With its aesthetically pleasing appearance, PRF-LCD-WRL perfectly fits the decor of interiors protected by the system.

- compatible with **PERFECTA** control panels (equipped with **PERFECTA-RF** module or **WRL** models)
- two-way encrypted radio communication at 433 MHz
- large and clear LCD display
- LEDs indicating the status of partitions and system
- quick activation of selected armed mode with function keys
- PANIC, FIRE, AUX alarms triggered from the keypad
- backlit display and keys
- audible signalling for selected system events
- power source:
  - two 3 V CR123A lithium batteries (required)
  - APS-055 5 V DC power supply (option)



Enclosure dimensions	139 x 124 x 22 mm
Operating temperature range	-10 °C...+55 °C
Weight	280 g
Maximum humidity	93±3%
Operating frequency band	433,05 ÷ 434,79 MHz
Radio communication range (in open area)	do 200 m m
Battery	2 x CR123A 3 V
Environmental class according to EN50130-5	II
Maximum current consumption, BT1 battery	55 mA
Power consumption in standby mode from BT1 battery	4 µA
Power supply voltage (power supply)	5 V DC
Maximum current consumption from the power supply	48 mA