

ANT-900/1800

The ANT-900/1800 dual-band antenna is designed to work in conjunction with the **GSM-4**, **GSM LT-1**, **GSM LT-2**, **GPRS-T1**, **GPRS-T2**, **GPRS-T4**, **GPRS-T6** modules as well as the **INTEGRA 128-WRL** control panel. The antenna comes with a standard SMA connector, so it can be also used in other devices provided with such a connector. The cable with a length of 2,5 meters and a magnetic base are used for easy mounting, even at some distance from the interacting device. This allows positioning of the antenna in a location with optimal GSM signal strength.

The antenna works in the following frequency bands: 900/1800 MHz.

- 900/1800MHz antenna for **GSM-4**, **GSM LT-1**, **GSM LT-2**, **GPRS-T1**, **GPRS-T2**, **GPRS-T4**, **GPRS-T6**, **INTEGRA 128-WRL** modules



Operating frequency	900/1800 MHz
Cable length	2.5 m
Impedance	50 Ohm
Cable	kabel koncentryczny RG174 (czarny)
VSWR	< 2.0
Operating temperature range	-20...+60 °C
Connector	SMA